

# **EP-1U SERIES**







#### **DESCRIPTION**

The E11EVEN power amplifier series are designed for the utmost clarity, dependability and will deliver under extreme usage. They have been meticulously designed with additional protection such as input sensitivity, voltage limiting and a hard or soft knee compressor. The E11EVEN power amplifiers are built with additional fans, cooling fins and protection to ensure they perform flawless under extreme conditions along with a 3-year limited warranty.

#### **KEY FEATURES**

- 4 channel high power amplifier
- Switching power supply
- · Switching amplification
- Integrated voltage limiters
- Thermal and current protection
- Short-circuit protection
- Standard and Bridge modes





## **SPECIFICATIONS**

SPECIFICATIONS	EP-60004	EP-13004	EP-28004	EP-34004	EP-50002		
Channels	4	4	4	4	2		
Output Power 8 Ω 4 Ω	4 x 300 W 4 x 600W	4 x 650 W 4 x 1300 W	4 x 1300 W 4 x 2300 W	4 x 2000 W 4 x 3400 W	2 x 3000 W 2 x 5000 W		
Output Circuitry	Switched Amplification						
Frequency Response	10 Hz-30 kHz						
Voltage Gain	23 – 44 dB (Rear DIPs adjustable)						
Controls	Power On/Off, Gain Pots, Rear DIP Switches						
Cooling	Front-to-Back						
Amplifier Protections	Thermal, Overload, Short Circuit, Over Current						
LED Indicators	Independent Channel Meters, Clip/VPL, Temp, Mute, VHF, On						
Audio Signal Input Connector		2 x Balanced Neutrik XLR					
Speaker Output Connector	4 x Neutrik NL4 2x Neutrik N						
Current Draw/Power Plug	-/15 A / N	EMA 5-15R	-/30 A / NEMA L5-30				

### **DIMENSIONS**

DIMENSIONS	EP-60004	EP-13004	EP-28004	EP-34004	EP-50002	
Dimensions (H x W x D)	1,7 x 19,0 x 15 in		1,7 x 19,0 x 18.5 in			
Net Weight	22,0 lbs		26,5			

